

50MS/s Four-Channel Arbitrary Waveform / Function Generator

PRELIMINARY

TABOR'S NEW

WW

WONDER WAVE SERIES

NEW

MODEL WW5064



- Four-channel 50MS/s waveform generator
- Sine and Square waves generated to 25MHz
- 16 Bit amplitude resolution
- 512k waveform memory, 1M waveform memory, optional
- 10 Separate sequences link and loop segments in user-definable order
- Four separate SYNC outputs for independent channel synchronization
- 10 Vpp into 50Ω, double into open circuit

- Multiple run modes including trigger, re-trigger and trigger delay
- (n)PSK and (n)QAM modulation
- High resolution 3.8" LCD, color display
- Ethernet 10/100, USB 2.0 and GPIB interfaces
- Multi-Instrument synchronization
- ArbConnection software for easy waveform creation&control

The Model 5064, is a four-channel universal waveform synthesizer. It is built in a small case size to save space and cost but without compromising bandwidth and signal integrity. The instrument outputs either standard or user-defined waveforms in the range of 100 mHz to 25 MHz. 16-bit DAC's are used for building waveforms with excellent accuracy and resolution which are suitable for the finest test signals that are needed for today's sensitive instruments. Using the latest technology, you can be assured that the features and capabilities of the Model 5064 will be useful for many years.

Signal Integrity

As technology is evolving and new devices are developed every day, faster signals are needed to simulate and stimulate these new devices. The 5064 provides the highest bandwidth in its class and hence providing accurate duplication and simulation of test signals. With its wide range of sample clock generator (up to 50 MS/s), 16-bit vertical

resolution and wide output bandwidth (over 25 MHz), one can create mathematical profiles, download the coordinates to the instrument and re-generate waveforms without compromising their fidelity and compatibility to the original design.

Four Synchronized Channels

The 5064 has four output channels of which are all synchronized to the same reference clock and share the same sample clock. This is not a limitation because the output frequency is a function of the number of points which are used for creating the waveform shape. On the other hand, the advantage of having four synchronized channels is huge in applications that require accurate and controlled phase between channels. Many applications require XY drive so two channels is just what is needed however, for three phase power simulation and four channel MEMS micro engine actuators, the Model 5064 is the most suitable product to use.

High Speed Function Generator

Care to use the instrument as a function generator? No need to fuss with loading complex waveform coordinates because the 5064 does the work for you. Select the standard waveforms tab and start generating any one from the ten waveforms that are pre-computed and available for immediate use. Included are: sine, triangle, square, pulse, ramp, sinc and others. Remember, however, that waveforms are created from sampling waveform points and therefore some of the waveforms cannot be generated above certain frequencies where the number of points are insufficient to draw a perfect shape. Regardless, using some trick, the 5064 will generate standard sine and square waveforms up to 25 MHz.

Stable and Accurate Output Signals

As standard, the instrument is equipped with a frequency reference that has 1ppm accuracy and stability over a period of 1 year. An external frequency reference is provided on the rear panel for applications requiring greater accuracy and stability.

Visit our website at www.taborelec.com


TABOR ELECTRONICS Inc.
Since 1971

50MS/s Four-Channel Arbitrary Waveform / Function Generator

Model WW5064



Waveform Memory and Memory Segmentation

Waveform memory is the internal "black board" where the waveforms are created and reside. Large memory bank provides for longer waveforms. One can use the entire memory for a single waveform or split the length to smaller segments. In this case, many waveforms can be stored in the same memory and replayed, one-at-a-time, when recalled to the output. The memory segmentation is combined with a sequence generator that can take different memory segments and link (and loop) them in any order as required for the test. The ability to loop waveform segments in a sequence saves a lot of memory space and hence, extends the capability of the generator to produce complex and much longer waveforms, which would otherwise require large banks of memory. The 5064 has four sequence generators that can be designed to generate unique sequences for each of its output channels.

Easy to use

Large and user-friendly 3.8" back-lit color LCD display facilitates browsing through menus, updating parameters and displaying detailed and critical information for your waveform output. Combined with numeric keypad, cursor position control and a dial, the front panel controls simplifies the often complex operation of an arbitrary waveform generator.

Remote Control

Access speed is an increasingly important requirement for test systems. Included with the instrument is a variety of interfaces: Ethernet, USB and GPIB so one may select the most suitable interface for the application. Remote control of instrument functions, parameters and waveform download is easily tailored to specific system environment regardless if it is just a laptop to instrument or full-featured ATE system. IVI drivers and factory support will speed up system integration and hence minimize time-to-market as well as significantly reduce system development costs.

Multi-Instrument Synchronization

Multiple 5064 can be synchronized using a Master-Slave arrangement allowing users to benefit from the same high quality performance in their multi-channels system.

Remote Calibration

Normal calibration cycles in the industry range from one to three years where instruments are sent to a service center, opened to allow access to trimmers, calibrated and certified for repeated usage. Leading-edge technology was implemented to allow calibration from any interface, USB, GPIB or LAN. Calibration factors are stored in a flash memory thus eliminating the need to open instrument covers.

ArbConnection

ArbConnection is a graphical tool that provides an unlimited source of waveforms. With the ArbConnection software you can control instruments functions, modes and features. You can also create a virtually infinite amount of test waveforms. Freehand sketch allows you to draw your own custom waveform for quick analysis of analog signals. You can use the built-in equation editor to create your own exotic functions. Add or subtract components of a Fourier series to characterize digital or analog filters or inject random noise into a signal to test immunity to auxiliary noise.

50MS/s Four-Channel Arbitrary Waveform / Function Generator

Model WW5064



Service and Support

Beyond providing precision Test & Measurement instruments, Tabor Electronics provides unparalleled service and support, and is continuously finding new ways to bring added value to its customers.

Our after-sales services are comprehensive. They include all types of repair and calibration, and a single point of contact that you can turn to whenever you need assistance. As part of our extensive support, we offer individualized, personal attention Help Desk, both online and offline, via e-mail, phone or fax.

Tabor Electronics maintains a complete repair and calibration lab as well as a standards laboratory in Israel and USA. Service is also available at regional authorized repair/calibration facilities.

Contact Tabor Electronics for the address of service facilities nearest you.

Applications

For expert technical assistance with your specific needs and objectives, contact your local sales representative or our in-house applications engineers.

Manuals, Drivers, and Software Support

Every instrument comes equipped with a dedicated manual, developer libraries, IVI drivers, and software. However, if your specific manual is lost or outdated, Tabor Electronics makes it possible to log-on to its Download Center and get the latest data "in a click".

Product Demonstrations

If your application requires that you evaluate an instrument before you purchase it, a hands-on demonstration can be arranged by contacting your local Tabor Electronics representative or the Sales Department at our Corporate Headquarters.

Five-year Warranty

Every instrument from the Wonder Wave series comes with a five-year warranty. Each one has full test results, calibration certificate, and CD containing product's manual and complete software package. Our obligation under this warranty is to repair or replace any instrument or part thereof which, within five years after shipment, proves defective upon examination. To exercise this warranty, write or call your local Tabor representative, or contact Tabor Headquarters and you will be given prompt assistance and shipping instructions.

CORPORATE HEADQUARTERS

9 Hatasia St. P.O.Box404,
Tel Hanan, Israel 20302
☎ +972 (4) 8213393
FAX: +972 (4) 8213388
www.taborelec.com

EUROPE

Austria
UEI-Vienna
☎ +43 15451 588
FAX: +43 15451 464

Benelux (Belgium, The Netherlands and Luxembourg)
BFI Optilas B.V.

☎ +31 172 44 60 60
FAX: +31 172 44 34 14

Bulgaria
New-Tek Ltd.
☎ +359 296 25286
FAX: +359 268 7110

Cyprus
Sprel Ltd.
☎ +357 2237 7159
FAX: +357 2237 7284

Czech Republic & Slovakia
Testovací Technika s.r.o.
☎ +420 2 7478 2237
FAX: +420 2 7478 1285

Denmark
Metric Industrial A/S
☎ +45 4371 6444
FAX: +45 4371 6433

Finland
Metric Industrial Oy
☎ +358 9 4761 600
FAX: +358 9 4761 6700

France
Racal Instruments SAS
☎ +33 1 3923 2205
FAX: +33 1 3923 2225

Germany
CompuMess Elektronika GmbH
☎ +49 89 321501-0
FAX: +49 89 321501-11

ADMess GmbH
☎ +49 6352 6091
FAX: +49 6352 1288

Greece
American Technical S.A.
☎ +30 210 5240 740
FAX: +30 210 5249 995

Hungary
ProMet Merestekhnika
☎ +36 24 521 240
FAX: +36 24 521 253

Italy
LP Instruments srl
☎ +39 2 4840 1713
FAX: +39 2 4840 1852

Norway
Metric Industrial AS
☎ +47 4000 4054
FAX: +47 4000 4053

Poland
NDN
☎ +48 22 641 1547
FAX: +48 22 644 4250

Romania
ARC Brasov srl
☎ +40 268 472 577
FAX: +40 268 419 749

Russia
Prist
☎ +7 495 777 5591
FAX: +7 495 236 4558

Spain & Portugal
Setup Electronica S.L.
☎ +34 93 414 0372
FAX: +34 93 414 0991

Sweden
Ferner Elektronik AB
☎ +46 8 760 8360
FAX: +46 8 760 8341

Switzerland
Elstar Elektronik AG
☎ +41 56 427 1888
FAX: +41 56 427 1976

United Kingdom & Ireland
SEMATRON UK Ltd.
☎ +44 1256 812222
FAX: +44 1256 812666

Yugoslavia (Bosnia, Croatia, Macedonia, Montenegro, Serbia, Slovenia)
MEM
☎ +43 1942 4254
FAX: +43 1943 4251

ASIA PACIFIC & JAPAN

Australia
Trio T&M Solutions
☎ +61 8 8234 0504
FAX: +61 8 8234 0130

India
AIMIL Ltd.
☎ +91 11 2695 0001
FAX: +91 11 2695 0011

Japan
TOYO Corporation
☎ +81 3 3279 0771
FAX: +81 3 3246 0645

South Korea
Zenixon Korea Co.
☎ +82 2 574 0084
FAX: +82 2 574 6447

Malaysia, Philippines & Thailand
Genetron Inc.

Malaysia
☎ +603 5513 3604
FAX: +603 5513 3608

Philippines
☎ +63 2672 0813
FAX: +63 2671 9490

Thailand
☎ +66 2948 7299
FAX: +66 2948 7322

New Zealand
Electrotest Ltd.
☎ +64 9 448 2600
FAX: +64 9 448 2611

Singapore & Vietnam
Gold Lite Engineering Pte Ltd.
☎ +65 6273 0487
FAX: +65 6273 5006

Taiwan, China & Hong Kong
LeColn Technology Co. Ltd.
☎ +886 2 8226 1366
FAX: +886 2 8226 1368

China & Hong Kong
☎ +86 21 5878 4585
FAX: +86 21 5878 4595

AFRICA

South Africa
Inala Technologies (Pty) Ltd.
☎ +27 11 206 8368
FAX: +27 11 206 8361

MIDDLE EAST

Israel
Lahat Technologies Ltd.
☎ +972 3 547 2741
FAX: +972 3 547 2742

Turkey
Netes Ltd.
☎ +90 216 340 5050
FAX: +90 216 339 5556

UNITED STATES SALES & SUPPORT OFFICE

☎ +1 909 797 0484
FAX: +1 760 751 1284

CANADA
Testforce Systems Inc.
☎ +1 514 856 0970
FAX: +1 514 856 6983

SOUTH AMERICAS
Tecnolink Electronics Co.
☎ +1 440 543 7710
FAX: +1 440 543 9681

Visit our website at www.taborelec.com


TABOR ELECTRONICS Inc.
Since 1971

Specification 50MS/s Four-Channel Arbitrary Waveform / Function Generator

Model WW5064



CONFIGURATION

Output Channels 4, semi-independent

INTER-CHANNEL CONTROL

LEADING EDGE OFFSET

Description: Channel 1 used as start reference channel 2, 3 and 4 can be offset by a programmable number of points.
Range: 0 to 1Meg, limited by n-8

Resolution and Accuracy: 1 point
Initial Skew: < 2ns

INTER-CHANNEL DEPENDENCY

Separate controls: Output on/off, amplitude, offset, standard waveforms, user waveforms, user waveform size, sequence table

Common Controls: Sample clock (Arb), frequency (Std), reference source, trigger modes, trigger advance source, SYNC output, Modulation

STANDARD WAVEFORMS

Waveforms: Sine, Triangle, Square, Pulse, Ramp, Sinc (Sine(x)/x), Gaussian, Exponential, Repetitive Noise, DC, Half-Cycle.

Frequency Range: Waveform dependent
Source: Internal synthesizer

SINE

Frequency Range: 100µHz to 25MHz

Start Phase Range: 0-359.95°

Start Phase

Resolution: 0.05°

Harmonics Distortion:

	< 3Vpp	< 5Vpp	< 10Vpp
DC to 1MHz	-55dBc	-48dBc	-37dBc
1 to 10MHz	-50dBc	-43dBc	-35dBc
10 to 25MHz	-35dBc	-30dBc	-28dBc

Non-Harmonic Distortion:

DC to 25MHz -65dBc

Total Harmonic Distortion:

DC to 20MHz 0.1%

Flatness (1kHz):

DC to 1MHz	1%
1MHz to 10MHz	3%
10MHz to 25MHz	5%

Phase Noise - Internal SCLK

100Hz Offset	-70dBc/Hz
1kHz Offset	-85dBc/Hz
10kHz Offset	-92dBc/Hz
100kHz Offset	-112dBc/Hz
1MHz Offset	-140dBc/Hz

TRIANGLE

Frequency Range: 100µHz to 6.25MHz

Start Phase Range: 0-359.9°

Start Phase

Resolution: 0.05°

SQUARE

Frequency Range: 100µHz to 25MHz

Duty Cycle Range: 0% to 99.9%

Rise/Fall Time: <8ns

Aberration: <5%+10mV

PULSE

Frequency Range: 100µHz to 6.25MHz

Delay, Rise/Fall Time,

High Time Ranges: 0%-99.9% of period (each independently)

Rise/Fall Time: <8ns

Aberration: <5%+10mV

RAMP

Frequency Range: 100µHz to 6.25MHz

Delay, Rise/Fall

Time Ranges: 0%-99.9% of period (each independently)

SINC (Sine(x)/x)

Frequency Range: 100µHz to 6.25MHz

"0 Crossings": 4-100

GAUSSIAN

Frequency Range: 100µHz to 6.25MHz

Time Constant: 10-200

EXPONENTIAL PULSE

Frequency Range: 100µHz to 6.25MHz

Time Constant: -100 to 100

REPETITIVE NOISE

Bandwidth: 25MHz

DC

Range: -10V to 10V

HALF-CYCLE WAVEFORMS

Function Shape: Sine, Triangle, Square

Frequency Range: 100Hz to 2MHz

Phase Start Range

(Sine/triangle only): 0 to 359.9°

Start Phase

Resolution: 0.05°

Run Modes: Continuous, Triggered

Delay Between Half Cycles

(Continuous only): 500ns to 21s

Delay Resolution 20ns

ARBITRARY WAVEFORMS

Sample Rate: 1.5S/s to 50MS/s

Vertical Resolution: 16 bits

Waveform Memory: 512k points (1M optional)

MEMORY SEGMENTATION

No. of Segments: 1 to 16k

Min. Segment Size: 16 points

Resolution: 4 points size increments from 16 to 512k points (1M optional)

SEQUENCED WAVEFORMS

Operation: Segments may be linked and repeated in a user-selectable order to generate extremely long waveforms. Segments are advanced using either a command or a trigger

ADVANCE MODES

Automatic Sequence

Advance: No trigger required to step from one segment to the next. Sequence is repeated continuously per a pre-programmed sequence table.

Stepped Sequence

Advance: Current segment is sampled continuously until a trigger advances the sequence to the next programmed segment and sample clock rate.

Single Sequence

Advance: Current segment is sampled the specified number of repetitions and then idles at the end of the segment. Next trigger samples the next segment the specified repeat count, and so on.

Specification 50MS/s Four-Channel Arbitrary Waveform / Function Generator

Model WW5064



Mixed Sequence

Advance: Each step of a sequence can be programmed to advance either a) automatically (Automatic Sequence Advance), or b) with a trigger (Stepped Sequence Advance).

Sequencer Steps: 1 to 4096

Segment Loops: 1 to 1Meg

Minimum Segment Duration: 500ns

Multi Sequence: Selectable sequence from 1 to 10

DIGITAL PULSE GENERATOR

Channel Dependency: All 4 channels share pulse parameters except level, polarity, delay and state

Pulse State: On/Off

Pulse Mode: Single or double, programmable

Polarity: Normal, inverted or complemented

Period: 320 ns minimum, programmed with 4 ns increments

Pulse Width: 8 ns minimum

Rise/Fall Time: <8ns

High Time: 0 ns minimum

Delay: 0 ns minimum

Double Pulse Delay: 0 ns minimum

Amplitude Window: 10mVp-p to 10Vp-p

Low Level -5V to +4.995V

High Level -4.995V to +5V

NOTES:

- All pulse parameters, except rise and fall times, may be freely programmed within the selected pulse period provided that the ratio between the period and the smallest incremental unit does not exceed the ratio of 512,000 to 1. With the 1M option, the ratio is extended to 1,000,000 to 1, hence the specifications below do not show maximum limit as each must be computed from the above relationship.
- Rise and fall times, may be freely programmed provided that the ratio between the rise/fall time and the smallest incremental unit does not exceed the ratio of 100,000 to 1.
- The sum of all pulse parameters must not exceed the pulse period setting

COMMON CHARACTERISTICS

FREQUENCY

Resolution: 12 digits (limited by 1μHz)

Accuracy & Stability: Same as reference

10MHz REFERENCE CLOCK

Internal 0.0001% (1 ppm TCXO) initial tolerance over a 19°C to 29°C temperature range; 1ppm/°C below 19°C and above 29°C;

External 1ppm/year aging rate
10MHz TTL, 50% ±2% duty cycle

AMPLITUDE

Range: 10mV to 10Vp-p into 50Ω;
Double into open circuit

Resolution: 4 digits

Accuracy (1kHz):

10mV to 99mVp-p ±(1% + 5mV)

100mV to 999mVp-p ±(1% + 10mV)

1V to 10Vp-p ±(1% + 70mV)

OFFSET

Range: 0 to ±4.995V, into 50Ω

Resolution: 1mV

Accuracy: ±(1%+1% of Amplitude +5mV)

FILTERS

Type: 25MHz Bessel
50MHz Bessel
60MHz Elliptic
120MHz Elliptic

OUTPUTS

MAIN OUTPUTS

Connectors: Front panel BNC, each channel

Impedance: 50Ω ±1%

Protection: Short Circuit to Case Ground, 10s max

Standby: Output On or Off (Output Disconnected)

SYNC OUTPUTS

Connectors: Rear panel BNC, separate for each channel.

Level: TTL

Sync Type: Pulse with Arbitrary and Standard Waves; LCOM in Sequence and Burst Modes

SAMPLE CLOCK OUTPUT

Connector: Rear panel SMB

Level: 400mVp-p

Impedance: 50Ω

COUPLE OUTPUT

Connector: Rear panel SMB

Level: LVPECL

Impedance: 50Ω, terminated to +1.3V

INPUTS

TRIGGER INPUT

Connector: Rear panel BNC

Impedance: 10kΩ

Slope: Positive or Negative (selectable)

Programmable Level: ±5V

Sensitivity: 100mV
Damage Level: ±12V
Pulse Width: >10ns minimum

EXTERNAL REFERENCE INPUT

Connector: Rear panel SMB

Frequency: 10MHz

Impedance&Level:

Default 10kΩ ±5%, TTL, 50% ±2% duty cycle

Option 50Ω ±5%, 0dBm Sinewave (with internal jumper)

SAMPLE CLOCK INPUT

Connector: Rear panel SMB

Input Level: 300mVp-p to 1Vp-p

Impedance: 50kΩ

Minimum Pulse Width: 4 ns

COUPLE INPUT

Connector: Rear panel SMB

Input Level: LVPECL

Impedance: 50Ω, terminated to +1.3V

Minimum Pulse Width: 4 ns

MODULATION

Carrier Waveform: Sinewave

Modulation Source: Internal

Run Modes: Off (Outputs CW), Continuous, Triggered, Delayed Trigger, Burst, Re-trigger and Gated

Advance Source: Front panel button, Software commands, Rear panel TRIG IN

(n)PSK and (n)QAM

Carrier Waveform: Sine wave

Carrier Frequency: 1Hz to 20MHz

Carrier Control: On/Off

Modulation Type: PSK, BPSK, QPSK, OQPSK, PI/4 DQPSK, 8PSK, 16PSK, 16QAM, 64QAM, 256QAM and User Defined

Symbol Rate Range: 1S/s to 1MS/s

Carrier Control: On/Off

Symbol Period Accuracy: ±(500ns + Carrier Period)

Table Size: 2 to 4096

TRIGGER CHARACTERISTICS

EXTERNAL

Source: Rear panel BNC

Trigger Level: ±5V

Resolution: 1mV

Input Frequency: DC to 5MHz

Min. Pulse Width: >10ns

Slope: Positive/Negative transitions, selectable

Trigger Jitter: ±1 sample clock period

Visit our website at www.taborelec.com

T
TABOR ELECTRONICS Inc.
Since 1971

Specification 50MS/s Four-Channel Arbitrary Waveform / Function Generator

Model WW5064



DELAYS (Trigger input to waveform output)

System Delay:	6 sample clock cycles+150ns
Trigger Delay:	[(0; 200ns to 20s) + system delay]
Trigger Resolution:	20ns
Trigger Delay Error:	6 sample clock cycles+150ns +5% of setting

INTERNAL

Retrigger Delay:	200ns to 20s, Waveform end to waveform restart
Retrigger Delay Error:	3 sample clock cycles+20ns +5% of setting
Retrigger Delay Resolution:	20ns

MANUAL

Source:	Soft trigger command through the front panel or external interface
----------------	--

GATED MODE

External signal enables generator. First output cyclesynchronous with the active slope of the triggering signal. Last cycle of output waveform always comple

BURST

Waveforms:	Sine, Triangle, Square, Pulse, Ramp, Sinc (Sine(x)/x), Gaussian Pulse, Exponential Fall, Rising Pulse, Noise, DC.
Counted Burst Cycles:	1 to 1Meg, programmable
Source:	Manual, Internal or External

FREQUENCY COUNTER / TIMER

Measurements:	Frequency, Period, Avaraged Period, Pulse Width and Totalize Trigger Input
Source:	Trigger Input
Range:	10Hz to 100MHz (typically 120MHz)
Sensitivity:	500mVpp
Accurcay:	1ppm
Slope:	Positive/Negative transitions
Gate Time:	100µSec to 1 Sec
Input Range:	±5V
Trigger Modes:	Continious, Hold and Gated
Period Avaraged	
Range	10ns to 0.1 Sec
Resolution	7 digits / Sec
Period and Pulse Width	
Range	200ns to 400 Sec
Resolution	100ns
Totalize	
Range	10 ¹² -1
Overflow	Led indication

MULTI-INSTRUMENT SYNCHRONIZATION

Description:	Multiple instruments can be daisy-chained together and synchronized to provide multi-channel synchronization.
Initial Skew:	<15 ns + 1 sample clock cycle, depending on cable length and quality, typically with 1m cables
Waveform Types:	Standard, Arbitrary and Sequenced using the automatic sequence advance mode only
Run Modes:	Continuous, Triggered, Gated and Counted Burst

LEADING EDGE OFFSET

Description:	Leading edge offset is programmable for master and slave units.
Run Mode:	Continuous run mode only
Offset Range:	200 ns to 20 s
Resolution&Accuracy:	20 ns

GENERAL

Power Supply:	85 to 265Vac, 48-63 Hz
Power Consumption:	60W
Front Panel Display:	Color LCD, 3.8" reflective, 320 x 240 pixels, back-lit
Operating temperature:	0°C - 50°C
Humidity (non-condensing):	11°C - 30°C 85% 31°C - 40°C 75% 41°C - 50°C 45%
Storage temperature:	-40°C to + 70°C.
Interface:	Ethernet 10/100, USB 2.0 and GPIB standard
Language:	IEEE-488.2 - SCPI – 1993.0
Dimensions:	212 x 88 x 415 mm (WxHxD)
Weight:	Approximately 7 lb
Safety:	EN61010-1, 2nd revision
EMC:	CE marked. Designed to meet VDE 0411/03.81 and UL 1244
Reliability:	MTBF per MIL-HDBK-217E, 25°C, Ground Benign
Workmanship Standards:	Conform to IPC-A-610D
Supplied Accessories:	Power Cord, USB cable, CD containing Operating Manual, ArbConnection software and developer libraries.
Warranty:	5 years standard

ORDERING INFORMATION

MODEL	WW5064
50MS/s Four-Channel ArbitraryWaveform Generator	
OPTIONS	
1Meg:	1 Meg Memory
ACCESSORIES	
S-Rack mount:	19" Single Rack Mounting Kit
D-Rack mount:	19" Dual Rack Mounting Kit
Case Kit:	Professional Carrying Bag

Note: Options and Accessories must be specified at the time of your purchase.